




# Belmont Linear High Bay Plug & Play (Zhaga)



120W and 180W



Linear High Bay

**STOP**

**READ THESE INSTRUCTIONS THOROUGHLY BEFORE INSTALLATION KEEP THESE INSTRUCTIONS FOR FUTURE REFERENCE.**

**IMPORTANT:**  
This product must be installed by a qualified electrician or competent person, and in accordance with current building and IET wiring regulations.

### BOX CONTENTS

This lighting fixture has been properly packed to avoid damage during transit. Before commencing with the installation carefully inspect the luminaire to confirm there is no damage. **DO NOT INSTALL** if any damage has occurred to the fixture or any of its components:

- Light Fitting
- Instruction Manual
- Suspension Kit

### TOOLS REQUIRED



## INSTALLATION INSTRUCTIONS

**1**

↓

**2**

**3**

Zhaga sensor

**4**

**Electrical connection wiring**

			NEUTRAL = Blue
			EARTH = Green/Yellow
			LIVE (SW) = Brown

↑

**PLEASE READ THESE INSTRUCTIONS BEFORE INSTALLATION.**

**WARNING: Risk of electric shock! Isolate the mains power before proceeding.**

- Turn off the mains power before performing inspections, installation, or removal
- Verify that the supply voltage is correct by comparing it with the luminaire label information
- It is the installers responsibility to ensure installation is suitable for the total load of the luminaire(s). The supply cable, fuses/circuit breakers must be correctly rated for the electrical load and considering for any transient inrush currents that may occur
- Do not perform insulation strength or resistance tests on installed luminaire(s) connected

1. Disconnect mains supply.
  2. Hang the light using supplied suspension cord. Recommend suitable carabiner clips for ease. (See weights overleaf)
  3. To add sensor, twist off blanking cap on the Belmont. Attach and twist in Zhaga sensor of your choice. Follow remote control instructions to set up sensor
  4. Connect mains cable and reconnect mains supply when deemed safe. **(4)**
- Note: sensors can only be adjusted when power is on



Manby Business Park, Manby, Lincolnshire, LN11 8UT  
Luminaire is a B&T Associates Ltd company.

Technical Helpline: +44 (0)1507 328031

www.lumineux.co.uk

### DISPOSAL

The light source of this unit is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.

Disassembly instructions for end of life disposal available on website.

Disposal of Electronic Equipment WEEE Directive 2002/96/EC This product falls within the scope of the Waste Electrical & Electronic Equipment Directive (WEEE), which means the product should not be disposed of as normal household waste. Please recycle where facilities exist or check with your Local Authority. RoHS - All components and materials used in this product are RoHS 2002/95/EC compliant.

Specifications may change from time to time. The information contained in this leaflet is for guidance only and should not be considered as always accurate and should be treated as not representative.

### WARRANTY


**This luminaire is warranted for a period of 5 years from the date of purchase.\*\*** The backup battery pack in the emergency version is warranted for a period of 24 months. The warranty could be invalidated should the light fitting not be installed according to these instructions, outside the scope of the specification or the product has been altered or tampered with in any way. Please see website for terms and conditions.

### PRODUCT TEMP SPECIFICATION

Standard -30° to +50°C  
Emergency 0 to +30°C

### BELMONT DIMENSIONS

Part No.	Description	Watts	L (mm)	W (mm)	H (mm)	Weight
430241-60	Belmont Linear High Bay 60° Optic - Grey	120W	340	325	60	3.5Kg
430242-60	Belmont Linear High Bay 60° Optic - Grey	180W	680	325	60	6.7Kg
430241-80	Belmont Linear High Bay 25° x 80° Optic - Grey	120W	340	325	60	3.5Kg
430242-80	Belmont Linear High Bay 25° x 80° Optic - Grey	180W	680	325	60	6.7Kg
430241-85	Belmont Linear High Bay 85° Optic - Grey	120W	340	325	60	3.5Kg
430242-85	Belmont Linear High Bay 85° Optic - Grey	180W	680	325	60	6.7Kg



For emergency wiring, please refer to the emergency pack instruction manual.

Installation Engineers Contact Details:		Luminaire Reference / Location
Name:	Tel:	

Luminaire Details:	Full Recharge Duration <b>24 Hours</b>	Emergency Duration <b>3 Hours</b>	Lamp Type <b>LED</b>
--------------------	--	-----------------------------------	----------------------

ROUTINE TEST RECORD										
Type Test	Year 1		Year 2		Year 3		Year 4		Year 5	
	Signed	Date								
Functional 1										
Functional 2										
Functional 3										
Functional 4										
Functional 5										
Functional 6										
Functional 7										
Functional 8										
Functional 9										
Functional 10										
Functional 11										
3hr Duration 12										

This product contains a light source of energy efficiency Class D.